

MACINTOSH COMPUTER	Mac Ixi, Ilsi	Macintosh LC, LC II - or - Performa 400, 405, 410, 430	Macintosh LC III, LC 475 - or - Performa 450, 460, 466, 467, 475, 476	Macintosh Ilvi, Ilvx - or - Performa 600, 600 CD	Macintosh LC 630, Performa 630 - or - Quadra 630	Macintosh Quadra 700, 900	Macintosh Quadra 605, 610, 650, 800, 950 - or - Centris 610, 650	Macintosh Quadra 840AV, 660AV - or - Centris 660AV	Power Macintosh 6100, 6100AV, 7100, 7100AV, 8100, 8100AV - with - DRAM Video Port (HDI-45) ***	Power Macintosh 7100, 8100 - with - VRAM Video Card (DB-15)	Power Macintosh 6100AV, 7100AV, 8100AV - with - AV Video Card (DB-15)	Macintosh PowerBook 160, 165, 165C, 180, 180C	Macintosh PowerBook 520, 520c, 540, 540c	Macintosh PowerBook Duo 210, 230, 250, 270c - with - Duo Dock - or - Duo MiniDock	Macintosh PowerBook Duo 210, 230, 250, 270c - with - Duo Dock II	Apple Display Card 4*8, 8*24, 8*24GC (revision B)	Apple Display Card 24AC
MITSUBISHI MONITOR			✓	✓	✓	✓	✓	✓	✓	✓	✓		✓		✓		✓
Monitor Model # THN 9105 Series Monitor Model # FR 8905 Series Monitor Model # TFG 8705 Series																	
640 x 480 @ 60 Hz	-	3,4	3,4	3,4	3,4	3,4	3,4	3,4	3,4	3,4	3,4	3,4	3,4	3,4	3,4	-	1,2,6 **
<u>640 x 480 @ 67 Hz</u>	<u>1,2</u>	<u>1,2</u>	1,2	<u>1,2</u>	1,2	1,2	1,2	1,2	1,2,5,6	1,2,6 *	1,2,6 *	1,2	<u>1,2,5,6</u>	1,2	1,2	-	1,2,6 *
800 x 600 @ 56 Hz	-	-	-	-	-	3,4 *	3,4 *	3,4 *	-	3,4 **	3,4 *	3,4 *	3,4 *	3,4 *	3,4 *	-	-
800 x 600 @ 60 Hz	-	-	-	-	3,4 *	-	-	-	-	-	-	-	-	-	-	-	1,2,6 **
800 x 600 @ 72 Hz	-	-	-	-	3,4 *	-	-	3,4 *	-	3,4 **	3,4 *	-	-	-	-	-	-
<u>832 x 624 @ 75 Hz</u>	-	-	<u>2,4</u>	-	<u>2,4</u>	<u>2,4</u>	<u>2,4</u>	<u>2,4</u>	<u>1,2,5,6</u>	<u>1,2,6 *</u>	<u>1,2,6 *</u>	<u>2,4</u>	<u>1,2,5,6</u>	<u>2,4</u>	<u>2,4</u>	<u>2,4 @</u>	<u>1,2,6 *</u>
1024 x 768 @ 60 Hz	-	-	-	-	-	-	-	3,4 *	-	3,4 **	3,4 *	-	-	-	-	-	1,2,6 **
1024 x 768 @ 70 Hz	-	-	-	-	-	-	-	3,4 *	-	3,4 **	3,4 *	-	-	-	-	-	-
1024 x 768 @ 75 Hz	-	-	-	-	-	-	-	2,3	-	2,3	-	-	-	-	-	-	1,2,6 *
1152 x 870 @ 75 Hz	-	-	-	-	-	<u>1,2,3,4</u>	<u>1,2,3,4</u>	<u>1,2,3,4</u>	-	<u>1,2,6 *</u>	<u>1,2,6 *</u>	-	-	-	<u>1,2,3,4</u>	<u>1,2,3,4</u>	<u>1,2,6</u>

640 x 480 @ 67 Hz
= Monitor Type:
"Macintosh Hi-Res Display"

832 x 624 @ 75 Hz
= Monitor Type:
"Macintosh 16" Color Display"

1024 x 768 @ 75 Hz
= Monitor Type:
"19" RGB Display"

1152 x 870 @ 75 Hz
= Monitor Type:
"Macintosh 21" Color"

Underlined item = Recommended setting.

* = Open the Monitors Control Panel and click the Options button to select this resolution. You may have to restart the computer if a new resolution has been selected from the monitor control panel.

** = You may have to hold down the option key on the keyboard while clicking the Options button in the Monitors Control Panel in order to access this video mode.

*** = DRAM Video Port requires Apple HDI-45 to DB-15 video cable (M2681LL/A). (Macintosh 6100/60 includes Apple HDI-45 to DB-15 cable.)

@ = Must have revision B of ROM on video board

- = Not a working combination.

✓ = Supports Apple Resolution switching software

Using Apple Resolution Switching Software

If apple resolution switching software is installed, you may access the following resolutions with the following DIP switch settings:

21" Multimode

1,2,6 = Set DIP switches 1, 2 and 6 "ON" (Supports 640 x 480 @ 67 Hz ; 832 x 624 @ 75 Hz ; 1024 x 768 @ 75Hz ; 1152 x 870 @ 75 Hz)

17" Multimode

1,2,5 = Set DIP switches 1,2 and 5 "ON" (Supports 640 x 480 @ 67 Hz ; 832 x 624 @ 75 Hz ; 1024 x 768 @ 75 Hz)

13" Multimode

1,2,5, 6 = Set DIP swiches 1, 2, 5 and 6 "ON" (Supports 640 x 480 @ 67 Hz & 832 x 624 @ 75 Hz)

* Once you have the correct adaptor settings, you can switch on the fly between available resolutions by going into the control panel, choosing monitors and clicking options. You must click on the "Rearrange on Close" box before you can use the resolution switching software.